

TEMCo

The most trusted name in phase converters

Tower Electric Motor Company

Rotary Phase Converter Electrical Specifications | Model size: 6000-1500W

TEMCo Heavy Duty Rotary Phase Converters provide utility quality 3-phase power converted from single phase power. TEMCo's world class products are being used throughout the US and internationally every day.

Common single to 3-phase conversion uses include:

- Machine Shops
- Woodworking
- Farm Equipment
- Restaurant Equipment
- Petrochemicals
- Home Hobbyist
- Oil Fields
- Irrigation
- High Tech
- Military
- Aerospace Industry
- Hospitals

TEMCo products meet the demands of tough industrial applications with dependability and quality.

Why choose TEMCo for your single to three phase needs?

- Run 3-phase equipment on single phase with a TEMCo Phase Converter.
- Rotary Higher quality lasts longer.
With minimal maintenance, requiring only periodic bearing grease, life expectancy is Indefinite.
- TEMCo is a member of the Better Business Bureau.
TEMCo is a company you can trust.
- Quiet & smooth operation
TEMCo's Phase Converters are known for their unusually cool, smooth and quiet running characteristics.
- Every TEMCo Phase Converter carries a 6-Year Warranty.
In fact, it's the longest warranty available, unparalleled industry wide.
- Proudly Made in the U.S.A.

Table no. 1	Series 6000 Model Sizes
1-phase input voltage	208-240V or 440-480V *
1-phase input frequency	60 Hz
3-phase output voltage	= 1 phase Volts + 10% on L3 (non Loaded)
3-phase output frequency	60 Hz
3-phase output voltage tolerance	±10%
3-phase output phase angle	120°
Rating	40C amb.-cont.
Ambient humidity	<95% (non-condensing)
Maximum altitude	3300 ft above sea level (see note 2)
Enclosure	Type 1

Table no. 2	Model	
	230V 6000-1500W	460V 6000-1500W
Maximum Medium run or start HP	1 HP	1 HP
Maximum Hard run or start HP	.66 HP	.66 HP
Maximum recommended group load HP	1.5 HP	1.5 HP
Continuous 3-phase output amps	5.1 amps	2.5 amps
Peak 3-phase output amps	6.8 amps	3.4 amps
Peak kW output	1500 watts	1500 watts
Peak 1-phase amps required	11.7 amps	5.8 amps
Approximate 1-phase idle amps	1.5 amp	.75 amps
1-phase breaker recommended	15 amps	15 amps
1-phase fuse recommended	12 amps (see note 1)	6 amps (see note 1)
Recommended 1-phase wire size	12 AWG	12 AWG
Recommended 3-phase wire size	12 AWG	12 AWG



* The default factory voltage configuration in this model is 208-240V. Units to be operated on 440-480V are built to order.

Note 1: Use only non time-delay fuses to protect this TEMCo Phase Converter

Note 2: De-rate TEMCo Phase Converter 20% for installation above 3300 feet altitude.

Call to order

Inside USA:
(800) 613-2290

USA & International:
(510) 490-2187

Fax:
(510) 490-1507

web:
www.phaseconverter.com

e-mail:
info@phaseconverter.com