



The most trusted name in phase converters

Tower Electric Motor Company

Rotary Phase Converter Electrical Specifications | Model size: 6500-5KW

TEMCo Heavy Duty Rotary Phase Converters provide utility quality 3-phase power converted from single phase power. TEMCo's world class products are being used throughout the US and internationally every day.

Common single to 3-phase conversion uses include:

- Machine Shops
- Woodworking
- Farm Equipment
- Restaurant Equipment
- Petrochemicals
- Home Hobbyist
- Oil Fields
- Irrigation
- High Tech
- Military
- Aerospace Industry
- Hospitals

TEMCo products meet the demands of tough industrial applications with dependability and quality.

Why choose TEMCo for your single to three phase needs?

- Run 3-phase equipment on single phase with a TEMCo Phase Converter.
- Rotary Higher quality lasts longer.
With minimal maintenance, requiring only periodic bearing grease, life expectancy is indefinite.
- TEMCo is a member of the Better Business Bureau.
TEMCo is a company you can trust.
- Quiet & smooth operation
TEMCo's Phase Converters are known for their unusually cool, smooth and quiet running characteristics.
- Every TEMCo Phase Converter carries a 6-Year Warranty.
In fact, it's the longest warranty available, unparalleled industry wide.
- Proudly Made in the U.S.A.

Table no. 1	Series 6500 Model Sizes
1-phase input voltage	208-240V or 440-480V *
1-phase input frequency	60 Hz
3-phase output voltage	= 1 phase Volts + 5% on L2 (non Loaded)
3-phase output frequency	60 Hz
3-phase output voltage tolerance	±5%
3-phase output phase angle	120°
Rating	40C amb.-cont.
Ambient humidity	<95% (non-condensing)
Maximum altitude	3300 ft above sea level (see note 2)
Enclosure	Type 1

Table no. 2	Model	
	230V 6500-5KW *	460V 6500-5KW *
Maximum Medium run or start HP	3 HP	3 HP
Maximum Hard run or start HP	2 HP	2 HP
Maximum recommended group load HP	5 HP	5 HP
Continuous 3-phase output amps	15.9 amps	7.9 amps
Peak 3-phase output amps	21.2 amps	10.6 amps
Peak kW output	5 kW	5 kW
Peak 1-phase amps required	36.7 amps	18.35 amps
Approximate 1-phase idle amps	5 amps	2.5 amps
1-phase breaker recommended	40 amps	20 amps
1-phase fuse recommended	35 (see note1)	15 amps (see note1)
Recommended 1-phase wire size	8 AWG	12 AWG
Recommended 3-phase wire size	10 AWG	12 AWG



- Model numbers followed by this asterisk are field re-configurable for 208-240V or 440-480V operation.

Note 1: Use only dual element time-delay fuses to protect this TEMCo Phase Converter

Note 2: De-rate TEMCo Phase Converter 20% for installation above 3300 feet altitude.

Call to order

Inside USA:
(800) 613-2290

USA & International:
(510) 490-2187

Fax:
(510) 490-1507

web:
www.phaseconverter.com

e-mail:
info@phaseconverter.com